

Gibson color code

For standard humbucker operation, you would tie the green and white leads together, and solder the black lead to ground, the red lead to the output.

To coil split and get the SCREW coil, you would wire a jumper to the junction of the green and white wires, and route that jumper to the HOT output, "shunting" the slug coil.

Bare ground wire

Coils-series for
Gibson tone

Slug coil - hot

Slug coil - negative

shunt lead

Screw coil - hot

Screw coil - negative

Coils-parallel for
"Fender-ish" tone

